

The Director Specifications

General Details

- 96 Channel programmable light controller
- 99 Individually selectable brightness levels
- Up to 250 software controlled dimming steps for smooth fading
- 15 programmable Chase sequences, each with 3 different modes of operation
- 4 'slider' controls
- 16 Assignable audio frequency channels (8 frequency and 8 composite channels)
- 7 Automatic pre-programmed music genres
- 72 scenes each using up to 96 channels
- 21 User-named, programmable and linkable sequences (8 scenes per sequence)
- 3 Programmable "EQ meter" effects
- Lightscape memory cards to save sequences, scenes and light shows
- 1 x 12v trigger input and 1 x 12v trigger output (wired)
- Programmable default mode for input trigger or remote PIR operation
- Programmable fade times from 1 second to 2 minutes
- Enables programming of chases, cross-fades and random lighting effects

Wireless Feature

- 433MHz radio frequency, cordless transceiver

Display

- 24 x 2 segment blue LCD display and matched blue LED indicators

Operating Voltage

- Low voltage unit, mains transformer supplied

Dimensions

- Height 80mm
- Width 250mm
- Depth 255mm